



CHAOYI INDUSTRIAL

Chaoyi's CBT24-6 Alarm Bell is low current, high sound output appliances for use in fire and burglary systems.

CBT24-6 operates on 24VDC and is motor driven.

Specifications

Rated Voltage : 24VDC

Rated Current : 25mA

Gong Diameter : 150mm (6"), iron

Sound Output : 85dB@3m

Operating Temperature : -10°C ~ +60°C

Operating Humidity : ≤95% R.H.

Weight : 660gm

Alarm Bell Model CBT24-6



Simplified Installation

1. Installed according to fire norms.
2. Remove the gong
3. Fix the bell on a 4" square electrical box with striker facing down
4. Connect the power
5. Replace the gong

Indoor Applications : Mount to standard 4" square electrical box

Outdoor Applications : Mount to waterproof back box